

Integrated WizarSwitch

IPC-1H



comm Integrated WizarSwitch (IPC Series) - Designed to control your Audiovisual Equipment in the most simplified ways via RS-232 commands; reasonably priced and works with most projectors and plasma displays.

One Touch Selection with LED Back-Lit Indications on the selectors' buttons, you can easily control your displays with its various selector buttons (e.g. select the different input source, volume and/or screen controls etc)

Widely used in Classrooms, Auditoriums, Lecture Theatres, Conference Rooms etc.

FEATURES

Display Controller for your Projector, Plasma (Power ON/OFF, input source selections, volume control) via RS232 Commands

One Touch Selection with LED Back-Lit Indications
16 sets of pre-programmed control protocols for the different displays models

Dip-Switch Settings Selections

Digital Volume Control for sound level adjustments

SELECTOR SWITCH (with LED Back-Lit Indications)

- Projector ON / OFF
- PC
- Video
- HDMI
- Wireless
- Blank (Toggle Button)
- Auto Sync (Toggle Button)
- Selector - For Motorised Screen
 (with Optional Relay Contact Module)
- Volume UP / DOWN (Built-In Digital Circuit)

SPECIFICATIONS

A) Input

- | | |
|-------------|-----------------------------|
| PC Signal | - VGA (D-Sub 15-Pin Female) |
| PC Audio | - 3.5mm Mini Jack |
| HDMI Signal | - HDMI Female |
| USB Type A | |
| USB Type B | |

B) Output

- | | |
|--------------|-------------------|
| PC Signal | - Terminal Block |
| HDMI Signal | - HDMI Female |
| Audio Signal | - 3.5mm Mini Jack |
| USB Type A | - Terminal Block |
| USB Type B | - Terminal Block |

C) Communication Control

- | | |
|--|------------------------------|
| Serial Control Port | - RS232 |
| Baud Rate | - 9600, 19200, 38400, 115200 |
| Data / Stop Bits | - 8 Bits / 1 Bits |
| | - No parity |
| Pre-programmed 16 sets of control protocols; | |
| - Selection through Dip-Switch Setting | |

D) Power

- DC 12V Power Adapter