

# Integrated WizarSwitch IPC-7AU

**NEW!**

**With Built-in HDMI to VGA  
and VGA to HDMI Converter!**



**comm Integrated WizarSwitch (IPC Series)** - Designed to control your Audiovisual Equipment in the most simplified ways via RS-232 commands; reasonably priced and works with most projectors and plasma displays.

One Touch Selection with LED Back-Lit Indications on the selectors' buttons, you can easily control your displays with its various selector buttons (e.g. select the different input source, volume and/or screen controls etc)

**Built-In HDMI to VGA and VGA to HDMI Converter that converts to the signal you require.** Widely used in Classrooms, Auditoriums, Lecture Theatres, Conference Rooms etc.

## FEATURES

**Display Controller** for your Projector, Plasma (Power ON/OFF, input source selections, volume control) via RS232 Commands

**One Touch Selection** with LED Back-Lit Indications  
**INPUTS : 1 HDMI, 2 VGA, 3 USB, 1 Video (Composite)**  
**OUTPUTS: 1 HDMI, 2 VGA, 2 USB, 1 Video (Composite)**

**Digital Volume Control** for sound level adjustments and MIC Inputs sound adjustments

### NEW Features!

- **STANDBY mode - MIC Volume Control usable**
- **PC1 with Audio: PC Monitor is usable even when Projector is OFF**
- **3 USB Connections**

### SELECTOR SWITCH

(with LED Back-Lit Indications)

- Display ON / OFF
- FUNCTION (Blank / Sync / Reset for HDMI)
- Screen / Audio Volume (UP / DOWN)
- Screen / Audio IN Selector
- HDMI / USB 1 IN Selector
- VGA / USB 2 IN Selector
- VGA / USB 3 IN Selector
- VIDEO / WIRELESS Selector

## SPECIFICATIONS

### A) Input

- |                  |                                  |
|------------------|----------------------------------|
| HDMI 1           | - HDMI with Audio Embedded       |
| VGA 2 / 3 Signal | - VGA (D-Sub 15-Pin Female)      |
| VGA 2 / 3 Audio  | - 3.5mm Mini Jack                |
| Video Signal     | - Composite Video (RCA)          |
| Audio Signal     | - Stereo / Composite Audio (RCA) |
| Microphone IN    | - 3.5mm Mini Jack                |
| USB 1 / 2 / 3 IN | - USB Female Type B Connector    |

### B) Output

- |                |                                     |
|----------------|-------------------------------------|
| HDMI           | - HDMI                              |
| VGA Signal     | - Monitor OUT, VGA Bandwidth 250MHz |
| Video Signal   |                                     |
| Audio Signal   |                                     |
| Microphone OUT |                                     |
| USB            |                                     |

### C) Communication Control

- |                     |                              |
|---------------------|------------------------------|
| Serial Control Port | - RS232                      |
| Baud Rate           | - 9600, 19200, 38400, 115200 |
| Data / Stop Bits    | - 8 Bits / 1 Bits            |
|                     | No parity                    |

### D) Power

- DC 12V Power Adapter

All products information and specifications are subject to changes without prior notice.