

Integrated WizarSwitch

IPC-8+



**With
Built-in
HDMI Selector
and Splitter Functions!**

comm Integrated WizarSwitch (IPC Series) - Designed to control your Audiovisual Equipment in the most simplified ways via RS-232 commands; reasonably priced and works with most projectors and plasma displays.

One Touch Selection with LED Back-Lit Indications on the selectors' buttons, you can easily control your displays with its various selector buttons (e.g. select the different input source, volume and/or screen controls etc)

Built-In HDMI Selector and Splitters Functions.

Widely used in Classrooms, Auditoriums, Lecture Theatres, Conference Rooms etc.

FEATURES

Display Controller for your Projector, Plasma (Power ON/OFF, input source selections, volume control) via RS232 Commands

One Touch Selection with LED Back-Lit Indications

INPUTS : 2 HDMI, 3 USB, 1 VGA

OUTPUTS: 2 HDMI, 2 USB, 1 VGA

Digital Volume Control for sound level adjustments

Volume Control Knob for MIC Inputs sound adjustments

NEW Features!

- **STANDBY mode - MIC Volume Control usable**
- **HDMI1 with Audio: PC Monitor is usable even when Projector is OFF**
- **3 USB Connections**

SELECTOR SWITCH

(with LED Back-Lit Indications)

- Display ON / OFF
- FUNCTION (Blank / Sync)
- Screen / Audio Volume (UP / DOWN)
- Screen / Audio IN Selector
- HDMI 1 / USB 1 IN Selector
- HDMI 2 / USB 2 IN Selector
- PC / USB 2/ WIRELESS Selector
- RESET for HDMI

SPECIFICATIONS

A) Input

- | | |
|---------------|-------------------------------|
| HDMI 1 / 2 | - HDMI with Audio Embedded |
| PC Signal | - VGA (D-Sub 15-Pin Female) |
| PC Audio | - 3.5mm Mini Jack |
| Microphone IN | - 3.5mm Mini Jack |
| USB 1 / 2 IN | - USB Female Type B Connector |
| USB IN | - USB Female Type A Connector |

B) Output

- | | |
|----------------|---------------|
| HDMI | - HDMI |
| HDMI | - Monitor OUT |
| PC Signal | |
| Audio Signal | |
| Microphone OUT | |

C) Communication Control

- | | |
|---------------------|------------------------------|
| Serial Control Port | - RS232 |
| Baud Rate | - 9600, 19200, 38400, 115200 |
| Data / Stop Bits | - 8 Bits / 1 Bits |
| | No parity |

D) Power

- | | |
|----------------------|--|
| DC 12V Power Adapter | |
|----------------------|--|

All products information and specifications are subject to changes without prior notice.