# Wireless Portable PA System

# **CWR-101**

## comm Dual Channel UHF Wireless Portable PA System **CWR-101H**

- ✓ Able to connect multiple units for larger. audience group, or for use in a larger area
- With 2 wired MIC input jacks and 2 wireless microphones
- ✓ With DVD slot with USB Player/ Digital MP3 Player/ DVD Player
- ✓ With Digital Recorder and Player that come with built in memory or by using SD Cards
- ON/OFF switch to save power
- ✓ Built-in Rechargeable Batteries Design



### **SPECIFICATIONS**

#### A) Wireless Receiver

Frequency Range

Frequency Stability

Sensitivity

Spurious Emission

Image and Spurious Rejection > 80dB

AF Output

SNR

Distortion

**Power Source** 

**Current Consumption** 

Modulation Mode

Channel Number

Frequency Response

#### **B) PA System**

**Output Power** 

Speaker

Recharge Time

Distortion

AF Frequency Response

Input Signal

**Output Signal** 

**Recharging Time** 

**Operating Time** 

UHF 400 ~ 900 MHz

± 0.0005%

-95dB S/N > 40dB

> 80dB

450mV ± 50mV

> 85dB

< 1%

**DC 12V** 

130mA ± 20mA

FM

1 CH / 16 CH

80Hz ~ 18KHz (± 3dB)

 $200W / 4\Omega$  Max, RMS  $100W/4\Omega$ 

Built-In Single 8" Woofer with 1" Compression Driver

**12V 7AH 2PCS** 

1% (at 10W)

50Hz ~ 18KHz (± 3dB)

2 X Wired MIC / 2 X Wireless MIC, 2 X AUX IN, 1 X VIDEO IN

1 X LINE OUT, 1 X VIDEO OUT,

1 x 1/4" phono jack (min 80hms speakers out)

10 ~ 12 Hours

3 ~ 4 Hours

All products information and specifications are subject to changes without prior notice.