Wireless Portable PA System

CWR-102H

- ✓ Dual Channel UHF
- ✓ Able to connect multiple units for larger audience group, or for use in a larger area
- ✓ With 2 wired MIC input jacks, 1 LINE input and 2 wireless microphones
- ✓ DVD slot with USB Player
- ✓ Built-in UHF 16 frequency receivers
- ✓ Voice Priority Switch
- ✓ ON/OFF Power switch to save power
- Come with battery and charging indicator
- Built-in Rechargeable Battery
- ✓ Built-in Retractable handle and wheels



Front View

SPECIFICATIONS Preliminary Datasheet

Model Number	CWR-102H
A) PA System	
Output Power	MAX 250W
Speaker	Built-In Single 10" Woofer with 1.5" Tweeter
AF Frequency Response	50Hz ~ 18KHz (± 3dB)
Input Signal	2 X Wired MIC
	1 X Aux In : 1/4"
	1 X Aux In : RCA (Stereo) / Mini-Jack
	2 X Wireless MIC
Output Signal	1 X Line Out (RCA)
	1 X Video Out (RCA)
Recharging Time	8 ~ 10 Hours
Operating Time	up to 10 Hours, using built-in battery
Battery Indicator	Single LED
Dimensions	345 (L) x 343(W) x 505 (H) mm
Weight	20 kg (includes battery)
B) Wireless Receiver	
Frequency Range	UHF 600 to 806 Mhz
Frequency Stability	± 0.0005%
Sensitivity	-95dB
Spurious Emission	55dB
SNR Rate	> 95dB
Channel Number	16 Channels





Wireless Mic

All products information and specifications are subject to changes without prior notice