

Voice Enhancement System CUR-101+CW5-BC

- ✓ Plug and Play with 1/4-inch (6.3mm) connector
- ✓ One-touch wireless sync connection
- ✓ ON/OFF Power indicator
- ✓ Built-in Lithium Rechargeable Battery
- ✓ Portable and lightweight
- ✓ Come with protective case for storage
- ✓ **Package Include:**
CW5-BC Bodypack transmitter
HM-1S Headset mic



SPECIFICATIONS

Model Number	CUR-101
A) Receiver	
Frequency Channel	UHF16 Frequency
Oscillation Mode	PLL Synthesized
Frequency Range	UHF 640 to 660 MHz
Receiving Sensitivity	-95dB
Spurious Emission	< 55dB
SNR Rate	> 95dB
6.3mm jack on receiver	To plug into input
USB	For charging
Indicator	LED Power, Charging and RF Signal
Built in Lithium battery	400mAh
Charge Time	2 to 3 hours
Working Time	3 to 4 hours
Operation Range	15m to 20m

B) Wireless Transmitter	
Wireless Transmitter	CW5-BC Bodypack transmitter with HM-1S Headset mic
Frequency Channel A	UHF16 Frequency
Frequency Channel B	UHF16 Frequency
Oscillation Mode	PLL Synthesized
Frequency Range	UHF 640 to 660 MHz
Receiving Sensitivity	-95dB
Spurious Emission	< 55dB
SNR Rate	> 95dB
Indicator	LED Power, Charging and RF Signal
Wireless Mic RF Output Power	10mW
Switch	Channel A or Channel B (Increase or Decrease Channel)
Battery	Type AA

C) Standard Package		Qty
1	CW5-BC Bodypack transmitter	1
2	HM-1S Headset Mic	1
3	6.33mm Receiver	1
4	USB cable for charging	1
5	3.5mm Male to 6.33mm Female adapter	1
6	AA battery	1
7	Protective Case for Storage	1



(7) Protective Case for Storage