

# Wireless Portable PA Amplifier

## CWR-1060W

- ➔ 60 watts of power
- ➔ Able to connect multiple units for a larger audience group
- ➔ **2 Wireless Microphone**  
Choose from 2 options :  
**Model : CW5-H** Handheld microphone x 2  
**Model : CW5-BC** Lavalier mic with bodypack transmitter x 2
- ➔ **One-touch** wireless frequency sync
- ➔ MP3 player with **Bluetooth** / USB / TF
- ➔ Built-in UHF 16 Frequency Receiver
- ➔ Voice Priority Switch
- ➔ ON/OFF Power switch to save power
- ➔ Come with battery and charging indicator
- ➔ Built-in Lithium Rechargeable Battery



Front View



Rear View

### SPECIFICATIONS

### Preliminary Datasheet

| Model Number                   | CWR-1060W   |
|--------------------------------|---|
| <b>A) PA System</b>            |   |
| Output Power                   | MAX 60W   |
| Speaker                        | Built-In 6" Full Range Speaker                            |
| AF Frequency Response          | 50Hz ~ 18KHz (± 3dB)                                      |
| Audio Input - Wired Mic        | 2 X MIC (1/4")  |
| Audio Input - Line-in          | 1 X Line In (3.5mm), 2 X RCA                              |
| Output Signal                  | 2 X Line Out (RCA)  |
| Voice Priority                 | Yes   |
| Power Supply AC                | 15V 1.5A Power Adaptor                                    |
| Power Supply DC & Battery      | 11.8V 4.4A Rechargeable Lithium battery                   |
| Recharging Time                | 9 ~ 10 Hours  |
| Operating Time                 | 8 ~ 10 Hours (estimation)                                 |
| Battery Indicator              | Battery level with charging status                        |
| Dimensions                     | 200 (L) x 230 (W) x 340 (H) mm                            |
| Weight                         | 4.0 kg (includes battery)                                 |
| Audio Player                   | MP3 player with Bluetooth / USB / TF                      |
| <b>B) Wireless Receiver</b>    |   |
| Wireless Microphone - Option 1 | Model : CW5-H Handheld microphone x 2                     |
| Wireless Microphone - Option 2 | Model : CW5-BC Lavalier mic with bodypack transmitter x 2 |
| Frequency Channel              | UHF16 Frequency   |
| Oscillation Mode               | PLL Synthesized   |
| Frequency Range                | UHF 640 to 680 MHz  |
| Receiving Sensitivity          | -95dB   |
| Spurious Emission              | < 55dB  |
| SNR Rate                       | > 95dB  |
| Indicator                      | LED RF Signal   |
| Wireless Mic RF Output Power   | 10mW  |

All products information and specifications are subject to changes without prior notice.