

# Portable PA Amplifier

## CWR-1060

- ➔ 60 watts of power
- ➔ Able to connect multiple units for a larger audience group
- ➔ **2 Wired Microphone** with 5m cable
- ➔ Input : 2 MIC (1/4") jack, 1 Line In (3.5mm), 2 RCA
- ➔ MP3 player with Bluetooth / USB / TF
- ➔ Built-in UHF 16 Frequency Receiver
- ➔ Voice Priority Switch
- ➔ ON/OFF Power switch to save power
- ➔ Come with battery and charging indicator
- ➔ Built-in Lithium Rechargeable Battery



Front View



Rear View

### SPECIFICATIONS

### Preliminary Datasheet

Model Number	CWR-1060
<b>A) PA System</b>	
Output Power	MAX 60W
Speaker	Built-In 6" Full Range Speaker
AF Frequency Response	50Hz ~ 18KHz ( $\pm$ 3dB)
Audio Input - Wired Mic	2 X MIC (1/4")
Audio Input - Line-in	1 X Line In (3.5mm), 2 X RCA
Output Signal	2 X Line Out (RCA)
Voice Priority	Yes
Power Supply AC	15V 1.5A Power Adaptor
Power Supply DC & Battery	11.8V 4.4A Rechargeable Lithium battery
Recharging Time	9 ~ 10 Hours
Operating Time	8 ~ 10 Hours (estimation)
Battery Indicator	Battery level with charging status
Dimensions	200 (L) x 230 (W) x 340 (H) mm
Weight	4.0 kg (includes battery)
Audio Player	MP3 player with Bluetooth / USB / TF
<b>B) Wired Mic</b>	
Microphone	2 X Wired Microphone with 5M cable

All products information and specifications are subject to changes without prior notice.